

Subject: ELECTRIC METER INSTALLATIONS

1. The HPUC owns and installs all meters. Customers are responsible for the expense, installation, and maintenance of all meter wiring and conduits, with the exception that the HPUC is responsible for it's wiring in current transformer installations.
2. Only one meter will be installed for each type of service as determined by voltage and phase. When more than one meter is installed on the same ype of service for the convenience of the HPUC, the sum of registrations will be taken as the total registration.
3. Meter boxes and cabinets must be placed so that the meter is five feet from the ground line unless a different location is specifically authorized by the HPUC. The location of the meter must be accessible at all times to the customer and to the HPUC. The customer s responsible for keeping the meter accessible – i.e snow removal, obstruction removal, etc.
4. The customer may have the meter placed on or in their switchboard with prior approval of the HPUC.
5. Grouped meter installations will be in compliance with the rules in the National Electrical Code.
6. Meters, service entrance switches, and current transformer cabinets are sealed by the HPUC, and the seals must not be tampered with or broken without the written approval of the HPUC.